

Model 3430-KuA

Ku-Band Beacon Tracking Receiver

A tracking receiver for antenna step tracking and automatic uplink power control

The Model 3430-KuA Version 4 is the latest release of our reliable series of 3430 Beacon Receivers. The Model 3430-KuA features an input of **11.7- 12.2 GHz**, Digital Level reference setting, Ethernet connectivity with M&C control interface, and power up temperature compensation for rapid signal acquisition. Frequency selection on 10 kHz steps may be accomplished from the front panel or via remote control. Pre-detection noise bandwidth of 50 kHz (or factory option of 25 kHz) facilitates accurate tracking at very low C/N levels.

- ★ Digital level reference setting, -40 to -100 dBm on 0.5 dB steps
- ★ Ethernet connectivity with M&C control interface
- ★ **NEW Version 2.0** M&C control interface allows for remote monitoring from one or multiple locations
- ★ RS-232/422/485 and Ethernet all Standard
- ★ Temperature stabilization compensation

The output of the Beacon Receiver is a DC voltage proportional to the input signal level to facilitate both antenna tracking control and automatic power control. A Loss of Carrier indicator is provided in the event the tracking signal is lost. Form "C" relay contacts provide an external Loss of Carrier Alarm. A front panel VFD or SSC GUI (via your computer) displays operating frequency, relative signal level, carrier lock or alarm, and input level.

Specifications

Input Frequency	11.7 -12.2 GHz
Input Level	-40 to -90 dBm typical
Level Adjust	Digital, 0.5 dB steps
Level Accuracy	±0.4 dB per step
 ±4 dB over entire range
External BDC or LNB included on Model – Ku Beacon Receivers	
LNB.....	WR-75 Flange
BDC	Type "SMA" Female
Output Connector	Type "F" Female
Tracking Slope	0.5 V/dB
Tracking Linearity	±0.25 dB
Frequency Selection	10 kHz steps
Min. input level for Lock	-105 dBm
Input Connector	Type "N" Female, 50 ohm*
Threshold	4 dB C/N for acquisition
	< 1 dB C/N for carrier lock
Tracking Response	0 to +10 VDC over 20 dB input range standard
	other ranges optional****
Alarms	Form-C relay contacts
AFC	±25 kHz**
Noise Bandwidth	50 kHz
M&C	RS-232 & RS-422/485
 Ethernet 10/100 Base T
 Continuous Data Streaming option/ streaming signal strength output via a dedicated RS-232 DB 9 connector

M&C ConnectorDB-9 Female & RJ 45 Connector

MECHANICAL:

Output Connector Modular socket & plug

Dimensions 1 RU, 19" x 16" x 1.75"

POWER:

Prime Input Power 90-260 VAC, 47-63 Hz,
auto-sensing, 45 Watts max

LNB Power +24 Volts @ 1 Amp available on center conductor
Selectable In/Out***

* Other input connectors available please contact SSC

** Other AFC options available please contact SSC

*** Other power options available please contact SSC

**** Other ranges available please contact SSC

Valid Options

Conversion Type

- Y LNB to be mounted at the Antenna with a WR-75 flange
- Z BDC with type “SMA” input connector



AFC and Filtering

- O Standard AFC and Standard 0.4 Hz output smoothing filter
- A No AFC – Use for tracking Wide Data Carriers. Standard 0.4 Hz output smoothing filter.
- S No AFC and No 0.4 Hz output smoothing filter.
- T No 0.4 Hz output smoothing filter. Standard AFC.

Bandwidth

- O 50 kHz pre-detection bandwidth.
- 5 25 kHz pre-detection bandwidth.

Input Connector on Rear of BTR

- N 50 ohm N female connector.
- B 50 ohm BNC female connector.
- Q 50 ohm TNC female connector.
- S 50 ohm SMA female connector.



M&C

- RS-232
- RS-422/485
- Ethernet 10/100 Base T with SSC Graphical User Interface
- Optional Continuous Data Streaming



Part Numbering Typical part number 3430-KuAYOON

Base Model	BAND	Conversion Type	Frequency Range	AFC & Filtering	Band-width	Input Connector
------------	------	-----------------	-----------------	-----------------	------------	-----------------

3430	KuA	Y or Z	11.7 -12.2 GHz	O, A, S, or T	0 or 5	N, B, Q or S
------	-----	--------	----------------	---------------	--------	--------------

Other Frequency Ranges are available.

Please see <http://www.satsyscorp.com> for more information.

Satellite Systems announces the new control GUI version **2.0** for our Beacon Receiver Product line. Enhanced control features and additional monitoring tools are included along with strip charting for signal strength, AFC, and temperature. Version 2.0 also includes a new event-triggered alarm feature that allows for email notification to your laptop or cell phone. Alarms are triggered via signal strength, loss of signal, and AFC conditions.

